


Specifications

Plug-in EQs: JXP-style

| 1.002 GHz MODELS | | | | | | |
|------------------|------------|-----------------|---------------------|----------|-------------------|------------------|
| PART NUMBER | VALUE (dB) | BANDWIDTH (MHz) | INSERTION LOSS (dB) | | EQ TOLERANCE (dB) | RETURN LOSS (dB) |
| | | | 45 MHz | 1002 MHz | | |
| N-ACC-LE-02 | 2 | 45-1002 | 2 | 1 | +/- 0.5 | ≥ 18 |
| N-ACC-LE-03 | 3 | 45-1002 | 3 | 1 | +/- 0.5 | ≥ 18 |
| N-ACC-LE-04 | 4 | 45-1002 | 4 | 1 | +/- 0.5 | ≥ 18 |
| N-ACC-LE-05 | 5 | 45-1002 | 5 | 1 | +/- 0.5 | ≥ 18 |
| N-ACC-LE-06 | 6 | 45-1002 | 6 | 1 | +/- 0.5 | ≥ 18 |
| N-ACC-LE-07 | 7 | 45-1002 | 7 | 1 | +/- 0.5 | ≥ 18 |
| N-ACC-LE-08 | 8 | 45-1002 | 8 | 1 | +/- 0.5 | ≥ 18 |
| N-ACC-LE-09 | 9 | 45-1002 | 9 | 1 | +/- 0.5 | ≥ 18 |
| N-ACC-LE-10 | 10 | 45-1002 | 10 | 1 | +/- 0.5 | ≥ 18 |
| N-ACC-LE-11 | 11 | 45-1002 | 11 | 1 | +/- 0.5 | ≥ 18 |
| N-ACC-LE-12 | 12 | 45-1002 | 12 | 1 | +/- 0.5 | ≥ 18 |
| N-ACC-LE-13 | 13 | 45-1002 | 13 | 1 | +/- 0.5 | ≥ 18 |




N-ACC-LE-02

* = EQ Value

Specifications

Plug-in EQs: JXP-style

| 1.218 GHz MODELS | | | | | | |
|------------------|------------|-----------------|---------------------|----------|----------------|-------------------------|
| PART NUMBER | VALUE (dB) | BANDWIDTH (MHz) | INSERTION LOSS (dB) | | FLATNESS (±dB) | RETURN LOSS IN/OUT (dB) |
| | | | 45 MHz | 1218 MHz | | |
| JXPEQLH-02 | 2 | 45-1218 | 2 | 1 | < 0.2 | 20 |
| JXPEQLH-03 | 3 | 45-1218 | 3 | 1 | < 0.2 | 20 |
| JXPEQLH-04 | 4 | 45-1218 | 4 | 1 | < 0.2 | 20 |
| JXPEQLH-05 | 5 | 45-1218 | 5 | 1 | < 0.2 | 20 |
| JXPEQLH-06 | 6 | 45-1218 | 6 | 1 | < 0.2 | 20 |
| JXPEQLH-07 | 7 | 45-1218 | 7 | 1 | < 0.2 | 20 |
| JXPEQLH-08 | 8 | 45-1218 | 8 | 1 | < 0.2 | 20 |
| JXPEQLH-09 | 9 | 45-1218 | 9 | 1 | < 0.2 | 20 |
| JXPEQLH-10 | 10 | 45-1218 | 10 | 1 | < 0.2 | 20 |
| JXPEQLH-11 | 11 | 45-1218 | 11 | 1 | < 0.5 | 18 |
| JXPEQLH-12 | 12 | 45-1218 | 12 | 1 | < 0.5 | 18 |
| JXPEQLH-13 | 13 | 45-1218 | 13 | 1 | < 0.5 | 18 |
| JXPEQLH-14 | 14 | 45-1218 | 14 | 1 | < 0.5 | 18 |
| JXPEQLH-15 | 15 | 45-1218 | 15 | 1 | < 0.5 | 18 |
| JXPEQLH-16 | 16 | 45-1218 | 16 | 1 | < 0.5 | 18 |
| JXPEQLH-17 | 17 | 45-1218 | 17 | 1 | < 0.5 | 18 |
| JXPEQLH-18 | 18 | 45-1218 | 18 | 1 | < 0.5 | 18 |
| JXPEQLH-19 | 19 | 45-1218 | 19 | 1 | < 0.5 | 18 |
| JXPEQLH-20 | 20 | 45-1218 | 20 | 1 | < 0.5 | 18 |



JXPEQLH-02

* = EQ Value